

BAJA Y MEDIA
FRECUENCIA

LOW & MID
FREQUENCY



15WR400

15WRS400

SM115/N

12SW1300Nd

12P1000Nd

12P80NDV2

MODEL	15WR400	15WRS400	SM115/N	12SW1300Nd	12P1000Nd	12P80NDV2
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400	400	400	1200	900	700
SENSITIVITY (dB 2.83v)	99	98	98	96	96	101
COIL DIAMETER	3	3	3	4	4	4
Fs (Hz)	36	35	35	45	47	45
Vas (liter)	224	233	267	45	49	77,1
Qts	0,3	0,33	0,38	0,26	0,26	0,15
Xmax (mm)	6,3	7,25	8	10	8	7,5
FREQUENCY RANGE (Hz)	35-4000	40-4000	35-3000	25-1800	30-2500	45-4000
MAGNET	Ferr	Ferr	Ferr	Nd	Nd	Nd
WEIGHT (Kg)	6,1	6,25	6,5	7,2	5,4	5,6



12P80FeV2

12LX60V2

12G40

12MC500

12MCS500

12MI100

MODEL	12P80FeV2	12LX60V2	12G40	12MC500	12MCS500	12MI100
DIAMETER (inches)	12	12	12	12	12	12
POWER (WAES)	700	700	500	500	500	450
SENSITIVITY (dB 2.83v)	100	96	97	98	97	100
COIL DIAMETER	4	4	3	2,5	2,5	3
Fs (Hz)	51	49	44	67	62	58
Vas (liter)	60,4	43,12	81	54,9	44	64
Qts	0,19	0,38	0,3	0,38	0,42	0,22
Xmax (mm)	7,5	9	5	8	8	2
FREQUENCY RANGE (Hz)	50-4000	35-2000	35-4000	50 - 5500	65-5000	40-4000
MAGNET	Ferr	Ferr	Ferr	Ferr	Ferr	Ferr
WEIGHT (Kg)	11,5	9,7	7,1	5,86	6	7,2



12LW30/N

12WR400

12WRS400

SM112/N

SM212

12BR70

MODEL	12LW30/N	12WR400	12WRS400	SM112/N	SM212	12BR70
DIAMETER (inches)	12	12	12	12	12	12
POWER (WAES)	450	400	400	400	350	125 RMS
SENSITIVITY (dB 2.83v)	96	97	97	97	97	93
COIL DIAMETER	3	3	3	3	2,5	2
Fs (Hz)	42	42	44	40	43	31
Vas (liter)	84	91,1	77,9	117,3	103	142
Qts	0,27	0,28	0,31	0,3	0,38	0,5
Xmax (mm)	6,3	7,25	6,3	7,25	8,25	8
FREQUENCY RANGE (Hz)	40-4000	45-5000	45-4000	40-4000	45-4000	25-4000
MAGNET	Nd	Ferr	Ferr	Ferr	Ferr	Ferr
WEIGHT (Kg)	3,9	5,5	5,5	5,65	4,6	3,6



10MC500

10MCS500

10LW30/N

10MCF400Nd

10G40

10MI100

10WR300

10WRS300

SM110/N

MODEL	10MC500	10MCS500	10LW30/N	10MCF400Nd	10G40	10MI100	10WR300	10WRS300	SM110/N
DIAMETER (inches)	10	10	10	10	10	10	10	10	10
POWER (WAES)	10	500	450	400	350	300	300	200	200
SENSITIVITY (dB 2.83v)	97	96	95	102	95	98	95	95	95
COIL DIAMETER	2,5	2,5	3	4	3	3	2	2	4
Fs (Hz)	60	70	55	270	45	50	47	52	43
Vas (liter)	26	18,8	28	1,8	49	54	50,5	39,3	65
Qts	0,28	0,37	0,29	0,45	0,3	0,21	0,29	0,38	0,35
Xmax (mm)	8	8	7	3,5	7	4,5	6	6	4
FREQUENCY RANGE (Hz)	60-5000	70-5000	55-4000	300-5000	45-4000	70-4000	50-5000	55-4000	45-6500
MAGNET	Ferr	Ferr	Nd	Nd	Ferr	Ferr	Ferr	Ferr	Ferr
WEIGHT (Kg)	5,7	5,7	3,75	6,2	5,7	7,1	3,5	3,5	3,5



10BR60V2

CM10

8P300Fe/N

8MC300Nd

8MI100

8LW30

8G40

MODEL	10BR60V2	CM10	8P300Fe/N	8MC300Nd	8MI100	8LW30	8G40
DIAMETER (inches)	10	10	8	8	8	8	8
POWER (WAES)	100 RMS	125	300	300	250	250	250
SENSITIVITY (dB 2.83v)	90,6	95	94	96	98	95	95
COIL DIAMETER	2	1,5	2,5	2	2	2,5	2,5
Fs (Hz)	31	61	51	76	90	70	70
Vas (liter)	108,2	40,7	26,3	11,6	13	16	17
Qts	0,47	0,51	0,32	0,28	0,56	0,37	0,36
Xmax (mm)	6,5	6,5	6	6	1	4,5	4,5
FREQUENCY RANGE (Hz)	30-5000	40-5000	50-8000	80-4000	150-7000	65-6000	65-6000
MAGNET	Ferr	Ferr	Ferr	Nd	Ferr	Nd	Ferr
WEIGHT (Kg)	2,87	2,93	4,03	1,9	3,1	2,35	3,3

www.beyma.com

0433610 - FOLLETO PRO 2017

BAJA Y MEDIA
FRECUENCIA

LOW & MID
FREQUENCY



21PW1400Fe

18SW1600Nd

18LEX1600Nd

18PW1400Fe

18P1200Nd/N

MODEL	21PW1400Fe	18SW1600Nd	18LEX1600Nd	18PW1400Fe	18P1200Nd/N
DIAMETER (inches)	21	18	18	18	18
POWER (WAES)	1400	1600	1400	1400	1200
SENSITIVITY (dB 2.83v)	98,5	97	97	98	98
COIL DIAMETER	4	5	4	4	4
Fs (Hz)	30	32	35	32	37
Vas (liter)	401,5	205,7	204,64	228,9	198
Qts	0,34	0,33	0,38	0,27	0,34
Xmax (mm)	10	10	14,5	10	9,5
FREQUENCY RANGE (Hz)	25-1800	25-1800	35-1000	25-1800	25-2000
MAGNET	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	19,9	11,4	9,5	16,9	8,5



18P1000FeV2

18PWB1000 Fe

18G550

18LX60V2

MODEL	18P1000FeV2	18PWB1000 Fe	18G550	18LX60V2
DIAMETER (inches)	18	18	18	18
POWER (WAES)	1200	1000	900	700
SENSITIVITY (dB 2.83v)	98	96	98	98
COIL DIAMETER	4	4	4,5	4
Fs (Hz)	33	30	36	35
Vas (liter)	230	265	210	236,52
Qts	0,32	0,40	0,37	0,476
Xmax (mm)	8	12,5	9	9
FREQUENCY RANGE (Hz)	30-2000	30-2000	25-1500	25-1000
MAGNET	Ferr	Ferr	Ferr	Ferr
WEIGHT (Kg)	13,8	13,6	12,6	11,7



18WRS600

SM118/N

15SW1300Nd

MODEL	18WRS600	SM118/N	15SW1300Nd
DIAMETER (inches)	18	18	15
POWER (WAES)	600	400	1300
SENSITIVITY (dB 2.83v)	98	97	97
COIL DIAMETER	3	3	4
Fs (Hz)	32	42	44
Vas (liter)	350	206	89,6
Qts	0,4	0,58	0,36
Xmax (mm)	8,5	7,25	10
FREQUENCY RANGE (Hz)	35-1000	40-4000	25-1800
MAGNET	Ferr	Ferr	Nd
WEIGHT (Kg)	8,7	7	7,7



15P1000FeV2

15P80Nd

15P80Fe/N

MODEL	15P1000FeV2	15P80Nd	15P80Fe/N
DIAMETER (inches)	15	15	15
POWER (WAES)	1000	800	800
SENSITIVITY (dB 2.83v)	98	100	101
COIL DIAMETER	4	4	4
Fs (Hz)	42	33	32
Vas (liter)	100,2	250	305
Qts	0,26	0,18	0,18
Xmax (mm)	8	7,5	7,5
FREQUENCY RANGE (Hz)	40-2000	25-4000	30-4000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	13,1	6	12,5



15LX60V2

15G40

15MC700

15LW30

15MC500

15MCS500

15MI100

MODEL	15LX60V2	15G40	15MC700	15LW30	15MC500	15MCS500	15MI100
DIAMETER (inches)	15	15	15	15	15	15	15
POWER (WAES)	700	700	700	500	500	500	450
SENSITIVITY (dB 2.83v)	98	97	98	98	98	97,5	100
COIL DIAMETER	4	4	3	3	2,5	2,5	3
Fs (Hz)	42	38	41	34	46	46	37
Vas (liter)	105,53	128	153	251	131,5	133,5	264
Qts	0,44	0,32	0,35	0,33	0,46	0,48	0,29
Xmax (mm)	9	9,5	9,8	7	8	8	4,5
FREQUENCY RANGE (Hz)	30-1500	40-1500	45-4000	35-4000	40-4000	50-4000	40-5000
MAGNET	Ferr	Ferr	Ferr	Nd	Ferr	Ferr	Ferr
WEIGHT (Kg)	10,2	10,4	7,5	4,5	6,2	6,2	7,8

BAJA Y MEDIA FRECUENCIA

LOW & MID FREQUENCY

MODEL	8WR250	8WRS250	SM108	8WOOFER/P V2	8BR40/N	CM8B	BF8R	6MI100
DIAMETER (inches)	8	8	8	8	8	8	8	6
POWER (WAES)	250	250	150	50 RMS	50 RMS	100 RMS	50 RMS	250
SENSITIVITY (dB 2.83v)	95	95	95	91	91	92,4	90	94
COIL DIAMETER	2	2	2	1	1,5	1,5	1	2
Fs (Hz)	62	68	71	35	30	73	52	128
Vas (liter)	17,7	12,5	14,4	59	89,1	14,6	29,6	3,07
Qts	0,24	0,27	0,32	0,50	0,39	0,62	0,92	0,51
Xmax (mm)	6	6	6	4,5	6,7	5,7	6	3
FREQUENCY RANGE (Hz)	65-4000	70-4000	70-6000	30-6500	35-6000	40-5000	30-6000	100-8000
MAGNET	Ferr	Ferr	Ferr	Ferr	Ferr	Ferr	Ferr	Ferr
WEIGHT (Kg)	3,9	3,25	3,1	1,3	1,35	2,18	1,17	2,2

MODEL	6P200Fe	6P200Nd	6MCF200Nd	6G40Nd	6G40Fe	605Nd	6MI90
DIAMETER (inches)	6,5	6,5	6,5	6,5	6,5	6,5	6,5
POWER (WAES)	200	200	200	170	170	125	125
SENSITIVITY (dB 2.83v)	93	92	97	95	94,3	100	96
COIL DIAMETER	2	2	2	2	2	1,5	1,5
Fs (Hz)	58	56	410	88	102	150	134
Vas (liter)	11,1	11,9	0,25	7,2	5	3	3,35
Qts	0,26	0,29	0,64	0,33	0,4	0,31	0,42
Xmax (mm)	5,5	5,5	2,5	3,1	0,42	2,5	2,5
FREQUENCY RANGE (Hz)	55-9000	60-9000	400-12K	70-9000	70-9000	150-8000	140-8000
MAGNET	Ferr	Nd	Nd	Nd	Ferr	Nd	Ferr
WEIGHT (Kg)	3,1	1,9	2,3	1,7	3	1,5	2,2

MODEL	6B30P	CM6	CP200Fe	5P200Nd	5G40Nd/N	5MP60/N	SK07
DIAMETER (inches)	6,5	15	5	5	5	5	-
POWER (WAES)	50 RMS	80 RMS	150	100	100	80	50
SENSITIVITY (dB 2.83v)	90	90,7	92	92	92	88	-
COIL DIAMETER	1	1,5	1,5	1,5	1,5	1	3
Fs (Hz)	56	138	72	78	140	63	47
Vas (liter)	15,6	2,47	5,6	4,5	1,45	5,77	-
Qts	0,5	0,93	0,33	0,3	0,45	0,46	-
Xmax (mm)	5,5	2,5	5,5	5,7	3	5,5	-
FREQUENCY RANGE (Hz)	55-8000	150-9000	70-10000	70-10K	150-17000	50-12000	20-100
MAGNET	Ferr	Ferr	Nd	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	1,25	2,16	2,2	1,24	1,3	1,2	1,5

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd
WEIGHT (Kg)	7,22	11,91	6,8	7,18	11,3	6,3

MODEL	10CX300Fe	8CX300Nd/N	8CX300Fe
DIAMETER (inches)	10	8	8
POWER (WAES)	300/50	250/50	250/50
SENSITIVITY (dB 2.83v)	96,5/104	96/104	96/104
COIL DIAMETER	2,5/1,75	2,5/1,75	2,5/1,75
Fs (Hz)	40	61	76
FREQUENCY RANGE (Hz)	50-20000	60-20000	80-20000
MAGNET	Ferr	Nd	Ferr
WEIGHT (Kg)	5,1	2,8	4,6

COAXIALES

COAXIALS

MODEL	15CX400Nd	15CX400Fe	15XA38Nd	12CX400Nd	12CX400Fe	12XA30Nd
DIAMETER (inches)	15	15	15	12	12	12
POWER (WAES)	400/90	400/80	350/90	400/90	400/80	350/90
SENSITIVITY (dB 2.83v)	98/105	98/105	99/105	98/105	96/105	98/105
COIL DIAMETER	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9	4/2,9
Fs (Hz)	40	40	33	42	42	35
FREQUENCY RANGE (Hz)	35-20000	35-20000	25-20000	40-20000	35-20000	35-20000
MAGNET	Nd	Ferr	Nd	Nd	Ferr	Nd</